



- Rigid matching network and circuit boards
- · Stainless steel mounting hardware



IA39A INTELLITAG™ RUGGED <u>AN</u>TENNA

Joining the diversified line of RFID readers are the Intermec Intellitag RFID antennas. The Intellitag RFID antenna family offers a variety of gain, polarization and radiation pattern options. This antenna is specifically designed for vehicle mount applica-

tions where shock and vibration can far exceed the specifications of antennas designed for fixed applications. Its pull-truded fiberglass radome makes it one of the toughest antennas on the market.

Description

915, 9.5 dBic, Cir Pol, N (RP)

Frequency Range

902 - 928 MHz

Gain

9.5 dBic

Impedance

50 Ohms

VSWR

<1.3:1

Axial Ratio

< 3 dB over entire half power beam

Polarization

Circular

Front-to-Back Ratio

> 15 dB

Maximum Input Power

100 Watts (at 50°C)

H-Plane Beamwidth

80 degrees (half power)

E-Plane Beamwidth

30 degrees (half power)

Connector

N Reverse Polarity

Cable Length

N/A

Weight

2358.6 grams (83.2 oz)

Dimensions

49 x 15.4 x 4.8 cm (19.3 x 6.1 x 1.9 in)


Mounting Hardware

203-734-001 kit included

203-733-001 kit order seperately

203-735-001 order seperately

203-737-001 order seperately



H-plane Azimuth pattern

E-plane Elevation pattern



North America

Corporate Headquarters 6001 36th Avenue West Everett, Washington 98203 tel: 425.348.2600 fax: 425.355.9551

550 2nd Street S.E. Cedar Rapids, Iowa 52401 tel: 319.369.3100 fax: 319.369.3453

Media Supplies

9290 Le Saint Drive Fairfield, Ohio 45014 tel: 513.874.5882 fax: 513.874.8487

Canada

7065 Tranmere Drive Mississauga, Ontario L5S 1M2 Canada tel: 905.673.9333 fax: 905.673.3974

Europe/ Middle East & Africa

Headquarters Sovereign House Vastern Road Reading RG1 8BT United Kingdom tel: 44.118.987.9400 fax: 44.118.987.9401

Asia

Asia Regional Office 26-16 International Plaza 10 Anson Road Singapore 079903 tel: 65.6324.8391 fax: 65.6324.8393

Beijing Representative Office

29 FL, Unit A1, China Merchant Tower 118 Jian Guo Road Chaoyang District, Beijing 100022 Tel: 86.10.5165.5922 Fax: 86.10.6567.6778

Australia

Level 4, 1-3 Atchison Street St. Leonards, NSW 2065 Australia tel: 61.2.9330.4400 fax: 61.2.9437.0204

South America & Mexico

Intermec South America Ltda. Rua Samuel Morse 120 9 andar Brooklin CEP04576-060 São Paulo, SP Brazil tel: 55.11.5502.6770

Intermec Technologies de Mexico Av Tamaulipas #141, Primer Piso Col. Hipodromo Condesa

Mexico, DF, 06140 Mexico tel: 525.55.241.4800 fax: 525.55.211.8121

Internet www.intermec.com

Sales 800.347.2636 (toll free in N.A.)

tel: 425.348.2726

Service and Support 800.755.5505 (toll free in N.A.) tel: 425.356.1799

Copyright © 2005 Intermec Technologies Corporation. All rights reserved. Intermec is a registered trademark of Intermec Technologies Corporation. All other trademarks are the property of their respective owners. Printed in the U.S.A. 611680-01A 10/05

In a continuing effort to improve our products, Intermec Technologies Corporation reserves the right to change specifications and features without prior notice.